

Coaxial, Adapter, BNC Female/Female



## LCAD30001

### Configuration

- BNC Female Connector 1
- BNC Female Connector 2
- Impedance 50 Ohm
- Straight Body Geometry

### Features

- Provides In-Series BNC to BNC Connections
- Operates to 4 GHz
- Max VSWR of 1.3:1
- Gold Plated Center Contacts

### Applications

### Description

These L-com RF Coaxial Adapters are used to interface between BNC to BNC with coaxial connections. The LCAD30001 is a straight adapter with a female to female configuration. This Coaxial Adapter, BNC Female / Female is made from brass and has a nickel finish. BNC adapters interface design is defined by Mil-STD-348A and has no tool required bayonet mount coupling mechanism with a robust center contact and outer conductor interface. BNC's generally work up to 3 GHz and are a cost effective way of insuring a highly dependable RF Coaxial connection. L-com's RF Coaxial and Triaxial adapters are in stock and ship same day.

### Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		4	GHz
VSWR			1.3:1	
Operating Voltage (AC)			500	Vrms

### Mechanical Specifications

Size		
Length	1.28in	32.51mm]
Width	0.38in	[9.65mm]

Description	Connector 1	Connector 2
Type	BNC Female	BNC Female
Polarity	Standard	Standard

### Material Specifications

	Connector 1	Connector 2

Coaxial, Adapter, BNC Female/Female



## LCAD30001

Description	Material	Plating	Material	Plating
Type	BNC Female		BNC Female	
Contact	Brass	Gold	Brass	Gold
Insulation	PTFE		PTFE	
Outer Conductor	Brass	Nickel	Brass	Gold
Body	Brass	Nickel	Brass	Nickel

### Environmental Specifications

#### Temperature

Operating Range -65°C to +165°C

**Compliance Certifications** (see [product page](#) for current document)

### Plotted and Other Data

Coaxial, Adapter, BNC Female/Female from L-com has same day shipment for domestic and International orders. Our portfolio includes coaxial cable assemblies, connectors, adapters and custom products as well as lightning and surge protectors, NEMA rated enclosures, and an RF product line which includes antennas, amplifiers, passive, and active components. The information contained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to implement improvements. L-com reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. L-com does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and L-com does not assume liability arising out of the use of any part or document.

The information contained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to implement improvements. L-com reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. L-com does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and L-com does not assume liability arising out of the use of any part or document.

Coaxial, Adapter, BNC Female/Female

L-com CAD Drawing

REVISIONS		
REV.	DESCRIPTION	DATE
A	INITIAL RELEASE	01/09/2020
		APPROVED SELLIS

  

$\phi .38$  [9.65]       $\phi .5$  [12]      1.3 [32.5]

THIRD-ANGLE PROJECTION

THE INFORMATION AND DESIGN IN THIS DOCUMENT IS THE PROPERTY OF L-COM GLOBAL CONNECTIVITY. ALL RIGHTS RESERVED.  
 SHEET 1 OF 1  
 SCALE N/A

**L-com**  
 an INFINITE brand  
 50 High Street, West Mill, 3rd Floor, Suite #30  
 North Andover, MA 01845 USA  
 Phone: 1.800.341.5266 | 1.978.682.6936  
 Fax: 1.978.689.9484  
 Website: www.L-com.com  
 E-mail: CustomerService@L-com.com

SIZE A    CASE CODE 43321    DRAWN BY BPUCHASKI    PART NUMBER LCAD30001    REV A

UNLESS OTHERWISE SPECIFIED LEADING DIMENSIONS ARE INCHES DIMENSIONS IN [ ] ARE MILLIMETERS  
 TOLERANCES:  
 .X = ±.2 [5.08]    FRACTIONS ± 1/32    ANGLES ± 1°  
 .XX = ±.02 [.51]    .XXX = ±.005 [.13]  
 CABLE LENGTH (L) TOLERANCES:  
 L ≤ 12 [305] = +1 [25] / -0  
 12 [305] < L ≤ 60 [1524] = +2 [51] / -0  
 60 [1524] < L ≤ 120 [3048] = +4 [102] / -0  
 120 [3048] < L ≤ 300 [7620] = +6 [152] / -0  
 300 [7620] < L = +5% / -0  
 ALL DIMENSIONS SHOWN ARE FOR REFERENCE ONLY.

THESE COMMODITIES, TECHNOLOGY OR SOFTWARE WERE EXPORTED FROM THE UNITED STATES IN ACCORDANCE WITH THE EXPORT ADMINISTRATION REGULATIONS. DIVERSION CONTRARY TO U.S. LAW PROHIBITED.